



Wattstopper  
PIR Wall Switch Occupancy Sensor  
Part No. PW-301-I-U



The PW-301 passive infrared (PIR) wall switch sensor can turn lights OFF and ON based on occupancy. It is characterized by high sensitivity to small and large movements, appealing aesthetics, and a variety of features.

## Features & Benefits

High sensitivity and dense coverage for exceptional performance

Defaults to Manual-ON operation for maximum energy savings

Color-matched lens and low profile for appealing design

Optional neutral connection with break off tab to expose neutral terminals

120/240/277 VAC and 347 VAC models

Allows multi-way control from one of up to four control locations

Allows multi-way control from one of up to four control locations

## Specifications

### General Info

Product Line	Wattstopper	Color	Ivory
UPC Number	754182938513	Country Of Origin	United States
Features	IR (Infrared), Motion Sensor	Switch Type	Motion Sensor
Application Sector	Commercial		

### Dimensions

Product Length US	2.73 in
-------------------	---------

### Technical Information

Response Frequency	50/60 Hz	Sensor Type	Occupancy
--------------------	----------	-------------	-----------

---

Number of Buttons	1	Amperage	4.3 A
Wattage	1200 W	Mounting Type	Box
Sensing Range	180 degrees, 1050 sq ft	Voltage	120/277 V
Connection Type	Wired	Load	1000W

---