

## Wattstopper 0-10V PIR Wall Switch Occupancy Sensor, 347V, Ivory

Part No. PW-311-347-I



The PW-311 passive infrared (PIR) dimming wall switch sensor can turn lights OFF and ON based on occupancy and allow the user to increase or decrease the lighting level. It works with 0-10 VDC dimming drivers and ballasts to control lighting loads including LEDs.

## Features & Benefits

Defaults to Manual-ON operation for maximum energy Neutral Sense™ connection option with break off tab to expose neutral savings terminals

Color-matched lens and low profile for appealing design

Supports Partial-ON operation for energy code compliance or incentives

120/240/277VAC and 347VAC models

Allows fully functional multi-way control from up to four switch locations

4.3 A

347.0 V

## **Specifications**

## General Info

Product Line	Wattstopper	Color	lvory
UPC Number	754182939091	Country Of Origin	China
Dimensions			
Product Width US	3.0 in	Product Weight US	0.5 lb
Product Volume US	37.5 cu in	Product Depth US	5.0 in
Product Height US	2.5 in		
Technical Information			

Amperage

Voltage

Occupancy

1500 W

Sensor Type

Wattage