

## Wattstopper Vacancy Sensor, 3-wire w/Nightlight, Ivory

Part No. RS-150BA-N-I



The RS-150BA-N Passive Infrared (PIR) Vacancy Sensor provides automatic shutoff for single-pole lighting control applications. It is engineered to comply with specific provisions of California's Title 24-2013 energy code.

## Features & Benefits

Complies with 2011 NEC requirements

Relay-based switching

Fixed 30-minute time delay; no adjustment necessary

Low-profile styling

Manual-on/automatic-off control

Integral LED nightlight

Integral LED nightlight

Replaces single-pole switches

Amber LED nightlight illuminates whenever connected load is off

Choice of five decorator colors; lens is color-matched to device

Ideal for bathrooms

Fixed 30-minute time delay

## **Specifications**

| General   | Info  |
|-----------|-------|
| Oction at | 11110 |

| Product Line       | Wattstopper                                 | Color             | lvory            |
|--------------------|---|-------------------|------------------|
| UPC Number         | 754182917297                                | Country Of Origin | China            |
| Features           | IR (Infrared), Motion Sensor,<br>Nightlight | Switch Type       | Motion<br>Sensor |
| Application Sector | Commercial                                  | Warranty Type     | 5-Year           |
| Dimensions         |   |                   |                  |
| Product Width US   | 4.0 in                                      | Product Weight US | 0.3 lb           |
| Product Volume US  | 63.0 cu in                                  | Product Depth US  | 5.0 in           |
| Product Height US  | 3.15 in                                     |                   |                  |

| Additional Information |                       |  |         |  |  |  |
|------------------------|-----------------------|--|---------|--|--|--|
| RoHS Conformant        | Yes                   | DesignLights Consortium Qualified System | Yes     |  |  |  |
| Security               | Yes                   |  |         |  |  |  |
| Technical Informati    | on                    |  |         |  |  |  |
| Response Frequency     | 60 Hz                 | Sensor Type                              | Vacancy |  |  |  |
| Number of Buttons      | 1                     | Amperage                                 | 5 A     |  |  |  |
| Indicator              | LED Light             | Wattage                                  | 600 W   |  |  |  |
| Sensing Range          | 180 degrees,600 sq ft | Voltage                                  | 120.0 V |  |  |  |
| Connection Type        | Wired                 |  |         |  |  |  |