



Wiremold  
2000 Flush Plate Adapter Fitting  
Part No. WH2051H



Feeds 2000 Series Raceway from an existing wall outlet. Equipped with 1/2" trade size threaded stud, toothed lock washer for grounding, and conduit bushing.

Features & Benefits

Feeds 2000 Series Raceway from an existing wall outlet. Equipped with 1/2" trade size threaded stud, toothed lock washer for grounding, and conduit bushing.

Specifications

General Info

|                   |   |                    |                  |
|-------------------|---|--------------------|------------------|
| Product Line      | Wiremold  | UPC Number         | 786776074369     |
| Country Of Origin | United States   | Application Sector | Commercial       |
| Standard          | cULus Listed Base & Blank Cover: File E4376<br>Guide RJBT. Multioutlet Assemblies: File E15191<br>Guide PVGT. Fittings: File E41751<br>Guide RJPR. Base & Blank Cover & Plugmold Series w/Snapcoil Harness: Meets Article 386 of NEC. Meets Section 12-3032 of CEC.<br>Plugmold Wired Sections: Meets Article 380 of NEC. Meets Section 12-3032 of CEC. |                    | Type<br>Plugmold |

Listing Agencies / 3rd Party Agencies

|                     |        |              |     |
|---------------------|--------|--------------|-----|
| cULus ListingNumber | E41751 | cULus Listed | Yes |
|---------------------|--------|--------------|-----|

Buy American Act Compliance

|       |     |
|-------|-----|
| NAFTA | Yes |
|-------|-----|

Additional Information

|                       |         |                               |                        |
|-----------------------|---------|-------------------------------|------------------------|
| RoHS Conformant       | Yes     | Product Environmental Profile | Yes                    |
| Technical Information |         |                               |                        |
| Amperage              | 15 A    | Enclosure Type                | Steel                  |
| Voltage               | 125.0 V | Environmental Conditions      | Dry interior locations |